



**Manual for the external Expression-Switch aka „Double-Preset“-
Switch, aka Favorite Switch
for Line6 Stompbox Modeler or M-Series:**

The Expression-Switch is simulating the toe-down and the heel-down position of an expression-pedal.

Attention! This switch does not work with the Line 6 Helix!

Workflow to guarantee full functionality!

- pull out the left/mono input-plug to switch off your unit
- connect the Expression-Switch with a stereo cable (TRS, 1/4" plugs) with your Line 6 device
- reconnect the left/mono input-plug to power up your unit
- choose a preset of your Line 6 Modeler and set your personal adjustments
- press the Expression-Switch (LED turns on)
- adjust one or more parameter of the same preset (all parameter except the model-selector can be changed)
- now you can switch between both adjustments
- then you should save your settings in your preset by pressing the chosen preset-footswitch until the LED is blinking.
- If you connect an expression pedal at the 1/4" (6,3mm) jack of your Stompbox Modeler/ M-Series, the internal expression-mod is not working.

Have a lot of fun with your unit and thank you very much for the confidence you have placed in us!

Stay Tuned!